

M784 UNIBUS RECEIVERS

**PDP-11
UNIBUS**

M SERIES

Length: Extended
Height: Single
Width: Single

Price:

\$30



Volts +5 GND	Power mA (max.) 200	Pins A2 C2, T1
--------------------	---------------------------	----------------------

R = BUS RECEIVER
B = CONNECTS TO UNIBUS

The M784 consists of 16 inverting receivers that are used as an output interface from the UNIBUS of the PDP-11.

SPECIFICATIONS

Input Loading: All inputs present one UNIBUS receiver load. (See UNIBUS description.)

Output Drive: Each output has a fan-out capability of 7 standard TTL loads.